



Frequency of Maintenance Testing Guide

Maximize the reliability and efficiency of your electrical assets

As an independent third party company, we are committed to providing objective, unbiased test results and recommendations. As a member of NETA, you are assured that all testing is performed objectively, according to NETA specifications, using calibrated instruments traceable to the National Institute of Standards and Technology (NIST).

Please use this complimentary guide to NETA-recommended maintenance testing frequencies and intervals to maximize the results of your reliability-based testing program. Trust High Voltage Maintenance to deliver the experience and results you can rely on.

Our Services Include:

- Commissioning and Startup
- Arc Flash Solutions
- Engineering Services
- Predictive Diagnostics
- Preventive Maintenance
- Partial Discharge Testing and Monitoring Solutions
- Smart Turnarounds and Outages
- Retrofit, Renewal, and Replacement Services
- Product Compliance & Conformity Testing
- Project Management
- Educational Services
- Emergency Response Services

Electrical power is the pulse of your facility. It's vital to your operations, but also dangerous and costly. When your electrical assets fail, profits and people can suffer.

In the Midwest and Northeast, rely on HVM to deliver the most complete solutions for electrical system reliability and safety. From testing for problems that could disable your system, to complete turnaround execution, you'll quickly understand how we are your single source solution for all your electrical reliability needs.

With 13 service locations in North America, HVM's experienced professionals are available where and when you need them. We'll help you build reliability programs from the beginning to get your process or plant moving toward maximum capacity and minimal risk of unexpected delays.



Frequency of Maintenance Tests



The InterNational Electrical Testing Association (NETA) recognizes that the ideal maintenance program is reliability-based and unique to each plant and each piece of equipment. The following schedule is a guide to NETA-recommended testing and maintenance intervals and should be used in conjunction with a qualified maintenance program.

For more than 50 years, High Voltage Maintenance has served as the industry leader providing safe, high quality electrical testing, maintenance, and engineering services to customers nationwide. We are an independent third-party testing company committed to providing objective, unbiased test results and recommendations. As a full member of NETA, you are assured that all our testing is performed objectively, according to NETA specifications, using calibrated instruments traceable to the National Institute of Standards and Technology (NIST).

This Frequency of Maintenance Testing Guide is a useful schedule of testing frequencies that correspond directly with the NETA Standard for Maintenance Testing Specifications. Specific condition, criticality, and reliability must be determined to correctly apply the matrix. Application of the matrix along with use of historical testing data and trending, leads to a quality electrical preventive maintenance program.

Inspections and Tests

(Frequency in Months)

Multiply the values listed in the table below by the factor in the Maintenance Frequency Matrix located to the right.

Maintenance Frequency Matrix

		Equipment Condition		
		Poor	Average	Good
Equipment Reliability Requirement	Low	1.00	2.00	2.50
	Medium	0.50	1.00	1.50
	High	0.25	0.50	0.75

Section	Description	Visual	Visual and Mechanical	Visual, Mechanical, and Electrical
7.1	Switchgear and Switchboard Assemblies	12	12	24
7.2	Transformers			
7.2.1.1	Small Dry-Type Transformers	2	12	36
7.2.1.2	Large Dry-Type Transformers	1	12	24
7.2.2	Liquid-Filled Transformers	1	12	24
	Sampling	-	-	12
7.3	Cables			
7.3.2	Low-Voltage Cables	2	12	36
7.3.3	Medium and High-Voltage Cables	2	12	36
7.4	Metal-Enclosed Busways	2	12	24
	Infrared Only	-	-	12
7.5	Switches			
7.5.1.1	Air, Low-Voltage Switches	2	12	36
7.5.1.2	Air, Medium-Voltage Metal-Enclosed Switches	-	12	24
7.5.1.3	Air, Medium- and High-Voltage Open Switches	1	12	24
7.5.2	Oil, Medium-Voltage Switches	1	12	24
7.5.3	Vacuum, Medium-Voltage Switches	1	12	24
7.5.4	Medium-Voltage SF ₆ Switches	1	12	24
7.5.5	Cutouts	12	24	24
7.6	Circuit Breakers			
7.6.1.1	Insulated-Case/Molded-Case CB	1	12	36
7.6.1.2	Air, Low-Voltage Power CB	1	12	36
7.6.1.3	Air, Medium-Voltage CB	1	12	36
7.6.2	Oil, Medium-Voltage CB	1	12	36
	Sampling	-	-	12
7.6.2	Oil, High-Voltage CB	1	12	12
	Sampling	-	-	12
7.6.3	Vacuum, Medium-Voltage CB	1	12	24
7.6.4	SF ₆ CB	1	12	12
7.7	Circuit Switches	1	12	12
7.8	Network Protectors	12	12	24
7.9	Protective Relays			
7.9.1	Electromechanical and Solid State	1	12	12
7.9.2	Microprocessor-Based	1	12	12
7.10	Instrument Transformers	12	12	36
7.11	Metering Devices	12	12	36
7.12	Regulating Apparatus			
7.12.1.1	Step-Voltage Regulators	1	12	24
	Sample Liquid	-	-	12
7.12.1.2	Induction Regulators	12	12	24
7.12.2	Current Regulators	1	12	24
7.12.3	Load Tap-Changers	1	12	24
	Sample Liquid	-	-	12
7.13	Grounding Systems	2	12	24
7.14	Ground-Fault Protection Systems	2	12	12
7.15	Rotation Machinery			
7.15.1	AC Induction Motors and Generators	1	12	24
7.15.2	Synchronous Motors and Generators	1	12	24
7.15.3	DC Motors and Generators	1	12	24
7.16	Motor Control			
7.16.1.1	Low-Voltage Motor Starters	2	12	24
7.16.1.2	Medium-Voltage Motor Starters	2	12	24
7.16.2.1	Low-Voltage Motor Control Centers	2	12	24
7.16.2.2	Medium-Voltage Motor Control Centers	2	12	24
7.17	Adjustable Speed Drive Systems	1	12	24
7.18	Direct-Current Systems			
7.18.1	Batteries	1	12	12
7.18.2	Battery Chargers	1	12	12
7.18.3	Rectifiers	1	12	24
7.19	Surge Arresters			
7.19.1	Low-Voltage Surge Protection Devices	2	12	24
7.19.2	Medium-and High-Voltage Surge Protection Devices	2	12	24
7.20	Capacitors and Reactors			
7.20.1	Capacitors	1	12	12
7.20.2	Capacitor Control Devices	1	12	12
7.20.3.1	Reactors, Dry-Type	2	12	24
7.20.3.2	Reactors, Liquid-Filled	1	12	24
	Sampling	-	-	12
7.21	Outdoor Bus Structure	1	12	36
7.22	Emergency Systems			
7.22.1	Engine Generator	1	2	12
	Functional Testing	-	-	2
7.22.2	Uninterruptible Power Systems	1	12	12
	Functional Testing	-	-	2
7.22.3	Automatic Transfer Switches	1	12	12
	Functional Testing	-	-	2
7.23	Telemetry / Pilot Wire SCADA	1	12	12
7.24	Automatic Circuit Reclosers & Line Sectionalizers			
7.24.1	Automatic Circuit Reclosers, Oil / Vacuum	1	12	24
	Sample	-	-	12
7.24.2	Automatic Line Sectionalizers, Oil	1	12	24
	Sample	-	-	12
7.27	EMF Testing	12	12	12





HVMcorp.com | HVM Headquarters, 5100 Energy Drive, Dayton, OH, 45414, USA | 1-866-HVM-TEAM (486-8326)

© 2021 Vertiv Group Corp. All rights reserved. Vertiv™ and the Vertiv logo are trademarks or registered trademarks of Vertiv Group Corp. All other names and logos referred to are trade names, trademarks or registered trademarks of their respective owners. While every precaution has been taken to ensure accuracy and completeness here, Vertiv Group Corp. assumes no responsibility, and disclaims all liability, for damages resulting from use of this information or for any errors or omissions. Specifications, rebates and other promotional offers are subject to change at Vertiv's sole discretion upon notice.